



# 5287

## Current Booster

*Datasheet*



# HAEFELY

Current and voltage – our passion

Designed by



# General Description

The type 5287 extends the performance of the C-tan  $\delta$  field test sets and MIDAS 2880 and MIDAS 2881.

It adds an additional high current power supply and nominal capacitor for on-site transformer short circuit impedance measurement.

The system is designed for on-site inductance testing, especially for short-circuit impedance testing at power transformers.

The short circuit impedance of a winding is tested with the opposite (secondary) winding shorted.

The requirement for the high current power supply and high accuracy measuring device is met with the 5287 in combination with MIDAS 2880 or MIDAS 2881.

The current output is automatically interrupted when the current booster is overloaded. The interrupt is indicated at the front panel. After sufficient cooling of the power supply the system turns back into normal operating mode. The test complies with IEC 60076-5.

Features	Advantages
<ul style="list-style-type: none"><li>▪ Portable</li></ul>	<ul style="list-style-type: none"><li><input checked="" type="checkbox"/> Convenient in on-site transport and measurement</li></ul>
<ul style="list-style-type: none"><li>▪ Compact design</li></ul>	<ul style="list-style-type: none"><li><input checked="" type="checkbox"/> Space saving</li></ul>
<ul style="list-style-type: none"><li>▪ Overload protection</li></ul>	<ul style="list-style-type: none"><li><input checked="" type="checkbox"/> Ensures safe operation</li></ul>

# Applications

Used for on-site inductance testing such as:

- Short-circuit impedance testing of power transformers

## Scope of Supply

- 5287 Current Booster including cables
- Operating Manual.



## Technical Data

Measurement	
Nominal Current Output	0 ... 10 A
Max. Current Output	15 A for 5 min
Voltage Output	0 ... 11 V or 0 ... 110 V
Standard C	approx. 100 nF

Mechanical	
Dimensions (W x D x H)	255 x 255 x 300 mm (10 x 10 x 11.8 in)
Weight	21 kg (46 lb)

## Global Presence

### Europe

HAEFELY AG  
Birsstrasse 300  
4052 Basel  
Switzerland

☎ + 41 61 373 4111  
✉ [sales@haefely.com](mailto:sales@haefely.com)

### China

HAEFELY AG Representative Office  
8-1-602, Fortune Street, No. 67  
Chaoyang Road, Beijing 100025  
China

☎ + 86 10 8578 8099  
✉ [sales@haefely.com.cn](mailto:sales@haefely.com.cn)

This document has been drawn up with the utmost care. We cannot, however, guarantee that it is entirely complete, correct or up to date.  
©Copyright HAEFELY/ Subject to change without notice

V2020.05



**HAEFELY**

Current and voltage – our passion



HIGH VOLTAGE



INSTRUMENTS



EMC

  
precision.  
**swiss made.**